


JKL LAMP NUMBER	VOLTS RATED	AMPS ±10%	MSCP ±25%	LUMENS ±25%	AVERAGE LIFE HRS.	FILAMENT TYPE
55	7.0	.410	2.00	25.14	500	C-2R
57	14.0	.240	2.00	25.14	500	C-2F
*257	14.0	.270	1.60	20.11	500	C-2R
1895	14.0	.270	2.00	25.14	2,000	C-2F

\* FLASHER TYPE LAMP.

NOTES:

1. FLASHER TYPE LAMPS HAVE A BI-METAL STRIP ADDED TO THE FILAMENT MOUNT TO PROVIDE THE FLASHING. HEAT FROM THE FILAMENT CAUSES THIS STRIP TO BEND AWAY FROM THE LEAD WIRE, BREAKING THE CIRCUIT. AS THE BI-METAL STRIP COOLS IT RETURNS TO ITS ORIGINAL POSITION AGAINST THE LEAD WIRE AND THE LAMP LIGHTS.
2. FLASHER TYPE LAMPS ARE DESIGNED TO RANDOMLY BLINK AT THE APPROXIMATE RATE OF 50-150 FLASHERS PER MINUTE AT NORMAL ROOM TEMPERATURE, SOME WILL BE OUTSIDE THIS RANGE. AS AMBIENT TEMPERATURE AND/OR INPUT VOLTAGE CHANGES, THE FLASH RATE MAY VARY CONSIDERABLY.

			<b>METRIC</b>  THIRD ANGLE PROJECTION		DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0		<b>JKL COMPONENTS CORPORATION</b>				
					TITLE		<b>G-4 1/2 SINGLE CONTACT BAYONET BASE LAMP</b>				
<b>B</b>	#57 FILAMENT C-2V TO C-2F	9/7/01	DRAWN BY	APPVD BY	DATE	SIZE	FSCM NO.	DRAWING NO.			
<b>A</b>	ADD NOTES	6/14/01	L. WENGSTROM	QC	9/7/01	<b>A</b>	<b>55335</b>	<b>BAYONET SINGLE CONTACT G-4 1/2</b>			
			- CAD DRAWING -		SCALE		RELEASED DATE		REVISION DATE	REV. NO.	SHEET
REV. NO.	DESCRIPTION/ECO NUMBER	APPVD DATE	MANUAL REVISIONS NOT PERMITTED		NONE		3/8/01		9/7/01	<b>B</b>	1 OF 1